

Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd

Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd

Solid State VSWR Deluxe Meter

Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd



rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

rgy Telecom (P) Ltd

Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd

Model VS-41 1 DX is the deluxe model of VSWR Meter model: VS-41 1 with additional features of Input Selector 'Crystal: Low & high, and Bolometer: low & high. It has a provision for output, which may be recorded.

Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd

Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd

Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd

Specifications:

Input power supply	220 VAC, \pm 10%, 50 Hz
Input Connector	BNC (F)
Amplifier type	High gain tuned at 1000 Hz
Input Frequency	1 000 Hz \pm 2%
Band width (3db)	50 Hz
Input selector	Xtal High (200KO) impedance Xtal Low (200O) impedance Bolo 200fl, 4.5 mA Bias Bob 200O, 8.7 mA Bias
Sensitivity	< 1 jjV for full scale deflection at Xtal low/ Bolo Position.
Range	Over 70 db (60 db in 10 db steps, 10 db through coarse adjustment, 2 db through fine adjustment)
Accuracy	\pm 0.2 db per 10 db step.
Meter scales	SWR 1-4, SWR 3-10 Expanded SWR 1-1.3 db 0-10 Expanded db 0-2
Mode	Normal / Expanded
Gain control	Coarse adjustment 10 db minimum Fine adjustment 2 db minimum
Recorder output	Through BNC (F) connector
Recorder output level	IV for full scale deflection of meter
Mechanical dimensions	26(L) X 13 (H) X 20.4 (D) cms
Weight	2.7 Kg.
Standard Accessories	i) Mains Cable (1 No.) ii) Coax. Cable BNC-BNC (1 No.) iii) Spare Fuses (2 Nos.) iv) Instruction Manual (1 No.)

Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd
Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd
Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd
Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd
Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd
Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd Synergy Telecom (P) Ltd

13-15 RPS flats, E-block, Vikaspuri, N Delhi-110018, India
Phone-91 11 28533349, Mobile-91 98101 38894, Fax -91 11 2853 1435,
E-mail : pradeep@rfconnectorhouse.com, Website : <http://www.rfconnector.info/>