

SYNERGY TELECOM P. LTD

40 watt single output DC- DC Converter



FEATURES

1. DC input 40V
2. High Efficiency, and high reliability.
3. Output protections: SCP/OVP/OLP/OPP
4. Wide operating ambient temperature (0°C ~ 50°C)
5. All using 105°C long life electrolytic capacitors.
6. 100% full load burn-in test

<i>Input Volt.</i>	48 VDC or others
<i>DC adjustment range</i>	+/- 10% (rated output voltage)
<i>Overload protection</i>	120% - 150% (rated load), Auto-recovery
<i>Over voltage protection</i>	110% - 150% (rated output voltage)
<i>short circuit protection</i>	long term
<i>Withstand voltage</i>	<i>Input- output:</i> AC 500V, 1 min <i>Input - Ground:</i> AC 500V, 1min <i>Output - Ground:</i> DC500V, 1 min
<i>Operating ambient</i>	0~45 degree Celcius, 20% ~ 90% RH (Non condensing)
<i>Safety standards</i>	EN60950, GB4943
<i>Dimension (L*W*H)</i>	145*59*38 mm
<i>Input Volt.</i>	48 VDC or others
<i>DC adjustment range</i>	+/- 10% (rated output voltage)
<i>Overload protection</i>	120% - 150% (rated load), Auto-recovery
<i>Over voltage protection</i>	110% - 150% (rated output voltage)
<i>short circuit protection</i>	long term
<i>Withstand voltage</i>	<i>Input- output:</i> AC 500V, 1 min <i>Input - Ground:</i> AC 500V, 1min <i>Output - Ground:</i> DC500V, 1 min

WZ-47 BUDHELLA VILLAGE, VIKASPURI, NEW DELHI – 110018

PHONE: 011-28533349, MOB: 9810138894/9212558066, FAX: 011-28533349

EMAIL: info@rfconnector.in, WEBSITE: <http://rfconnector.in/>