

# Synergy Telecom P Ltd.

**SP3T Terminated  
P3 Series  
DC - 26.5 GHz  
SMA (F) Connectors  
Failsafe, Latching, Momentary**



## SPECIFICATIONS

FREQ. (GHz)	DC - 2.0	2.0-4.0	4.0-8.0	8.0-12.4	12.4-18.0	18.0-26.5
VSWR	1.20:1	1.20:1	1.25:1	1.30:1	1.40:1	1.50:1
INSERTION LOSS	0.20	0.20	0.25	0.30	0.40	0.60
ISOLATION	90	80	80	70	60	50
IMPEDANCE	50 Ohms					

MECHANICAL	
CONTACT	BREAK BEFORE MAKE
ACTUATOR	FAILSAFE, LATCHING, MOMENTARY
SWITCHING SPEED	20 mSEC MAX
ELECTRICAL	
ACTUATOR VOLTAGE	12.0, 15.0, 24.0, 28.0 Vdc
ACTUATOR CURRENT	VARIES UPON ACTUATOR VOLTAGE - CONTACT CEI
POWER HANDLING	200 WCW @ 1.0 GHz

<b>TERMINATION</b>	8 WATTS MAX.
<b>ENVIRONMENTAL</b>	
<b>OPERATING TEMP</b>	-40 DEG C TO 90 DEG C ( <b>STANDARD</b> ) -54 DEG C TO 90 DEG C (OPT /MS **)
<b>SINE VIBRATION</b>	30 G'S rms
<b>LIFE</b>	1,000,000 CYCLES
<b>RANDOM VIBRATION</b>	20 G'S rms
<b>FINISH</b>	
<b>RF CAVITY</b>	ALUMINUM, ELECTROLESS NICKEL PLATED PER MIL-C-26074, CLASS 4 UNLESS LOW OR ULTRA LOW PIM
<b>ENCLOSURE</b>	ALUMINUM, BLUE OR BLACK
<b>CONTACT</b>	BERYLLIUM COPPER, GOLD PLATED PER MIL-G-45204
<b>CONNECTOR SHELL</b>	CRES, PASSIVATED PER QQ-P-35 OR BRASS, ELECTROLESS NICKEL PLATED PER MIL-C-26074

13-15 RPS flats, E-block, Vikaspuri, N Delhi-110018, India  
Phone-91 11 28533349, Mobile-91 98101 38894, Fax -91 11 2853 1435,  
E-mail : pradeep@rfconnectorhouse.com, Website : <http://www.rfconnector.info/>