

# Synergy Telecom P Ltd.

## BNC F TO SMA F ADAPTOR

Part no-ST01BSFF006



---

### Electrical:

Characteristic Impedance	50 ohm
Frequency Range	DC-4 GHz
VSWR	$\leq 1.20$ @DC-4 GHz
Insertion Loss	$\leq 0.10$ dB

---

### Mechanical:

Durability	Mating Cycles $\geq 500$
------------	--------------------------

---

### Material and Plating:

	Material	Plating
Body	Brass	Ni
Insulator	PTFE(Teflon)	-
Center conductor	Phosphor Bronze	Gold

---

WZ-47 BUDHELLA VILLAGE ,VIKASPURI NEW DELHI-110018  
Phone: 011-28533349, Mob: 9810138894/9212558066, Fax: 011-28533349  
Email:- info@rfconnector.in, Website:- www.rfconnector.in

# Synergy Telecom P Ltd.

## **Environmental:**

Operating Temperature Range

-40°C ~ +85°C

RoHs

Compliant

Weatherproof Rate

IP 67

WZ-47 BUDHELLA VILLAGE ,VIKASPURI NEW DELHI-110018

Phone: 011-28533349, Mob: 9810138894/9212558066, Fax: 011-28533349

Email:- [info@rfconnector.in](mailto:info@rfconnector.in), Website:- [www.rfconnector.in](http://www.rfconnector.in)